

FM Transmitter

The Broadcastvision Entertainment FM Transmitter is the most universal entertainment solution available. With a transmission range of more than 30,000sq/ft the FM transmitter provides high quality audio transmission for maximum reception. Broadcast audio wirelessly from a TV or any audio source with an audio output jack. Part 15 FCC Certified #PG2-TDA123GGT.



Transmitter mounting
bracket included

Features

- Includes power supply, audio cables (3.5mm-rca, digital optical), tune to sign (w/ vinyl numbers) & mounting bracket.
- Fully selectable through fm-band (88.1 – 107.9).
- Transmission range 25,000+ square feet – 300 feet line of site.
- High visibility digital led interface for maximum ease-of-use.
- Option for 100khz and 200khz channel spacing selection.
- Line level stereo input.
- High fidelity stereo audio.
- Adjustable audio input modulation level.
- Modulation level indicator.
- Stereo on/off selection.
- Telescoping and rotational antenna for maximum application flexibility.
- Optional - BNC interface available for extended antenna capabilities.
- Audio in: analog rca-3.5mm ,digital coax & digital optical.
- Power requirements: 12v, 300ma, 2.1mm barrel connector.
- input impedance: 1K
- Level gain control: 20 mv to 1V
- Transmission freq: 88.1-107.9MHz
- Dimensions: 5.5" w x 1.5" h x 4.75" d
- Weight: 10 oz.
- 5-year warranty

Call or email us today for more information:

888.330.4283 (4BVE) Sales@broadcastvision.com